



## Grandstream Networks, Inc.

126 Brookline Ave, 3rd Floor  
Boston, MA 02215. USA  
Tel : +1 (617) 566 - 9300  
Fax: +1 (617) 249 - 1987  
[www.grandstream.com](http://www.grandstream.com)

For Warranty and RMA information, please visit  
[www.grandstream.com](http://www.grandstream.com)



## In-Wall Mounting Kit

### Quick Reference Guide

(GDS3710/3705 NOT Included)

**Content**

---

English.....1

## PRECAUTIONS

- Please follow local building code and electrical code to install the device.
- Suggest to install the device with bottom line 45~55 inches (1.2~1.4 meters) above the ground level.
- Please avoid dropping or vigorous vibrating of the device.
- Please keep device away from strong electromagnetic field or explosive atmosphere.
- Do not open or install the device in damp environment. Avoid using the device in very low or high temperature environment.
- Recommend to seal the frame or wall gap with silicone or other sealant after installation to avoid inside water leaking.
- Remove the electrostatic adsorption protective plastic film after all installations/configurations to avoid lens cover contamination or scratch.
- Please refer to Grandstream website for more updated Online Documents like:

### QIG:

[www.grandstream.com/sites/default/files/Resources/GDS3705\\_QIG.pdf](http://www.grandstream.com/sites/default/files/Resources/GDS3705_QIG.pdf)

[www.grandstream.com/sites/default/files/Resources/GDS3710\\_QIG.pdf](http://www.grandstream.com/sites/default/files/Resources/GDS3710_QIG.pdf)

### User Manual:

[www.grandstream.com/sites/default/files/Resources/GDS3705\\_UserManual.pdf](http://www.grandstream.com/sites/default/files/Resources/GDS3705_UserManual.pdf)

[www.grandstream.com/sites/default/files/Resources/GDS3710\\_UserManual.pdf](http://www.grandstream.com/sites/default/files/Resources/GDS3710_UserManual.pdf)

### FAQ:

[www.grandstream.com/our-products](http://www.grandstream.com/our-products)

*The warranty not apply to defects and failures as a result of improper installation.*


*The manufacturer is neither liable for damages caused by theft within an area that is accessible after the attached electric lock is switched. The product is not designed as a burglar protection device except when used in combination with a standard lock.*

*If the proper mounting instructions not met, water might get in and destroy the electronics as the internal circuits are under continuous operation.*


*The manufacturer's warranty shall be void for products damaged in this way.*

**This guide applies to both GDS3705 and GDS3710, with GDS3710 in the illustration.**


# PACKAGE CONTENTS



1 x Plastic Box



1 x Cover Plate



1 x Drill Template



(1)

PA3.5\*35mm

6 x Anchor & Screw Set (Mount the Plastic Box into Solid Wall)



(2)

PM3\*10mm

6 x Screws (Fix the Bracket into Plastic Box)



(3)

PM3\*12mm

6 x Screws (Fix Plastic box on Meta Frame)



1 x Metal Frame (For Stud Mount)



1 x Quick Reference Guide



1 x Anti-Tamper Hex Key



(4)

M3

6 x Nuts (Fix Plastic Box on the Meta Frame)



(4)

M3

6 x Nuts (Fix Plastic Box on the Meta Frame)



(5)


PM3\*12mm

6 x Anti-Tamper Screws

## Solid Wall Installation


Please follow below steps to install the device into solid wall.

**Step 1:** Use provided Drill Template to mark boundary then drill holes for the 6 mounting screws and the circular hole for wiring. (drilling or dig tools not provided) Then dig a rectangle hole for the box with depth around **38~43 mm (or 1.50~1.69 inch)**, refer to mark in the template (rotating it to measure if necessary).




.5.

**Step 2:** Mount the Installation Bracket into the Plastic Box using supplied Screws(2).




**Step 3:** Use provided Anchor/Screw(1) to mount the Plastic Box inside the hole just digged.




.6.


**Step 4:** Remove the frame back cover (designed for Surface/ OnWall Installation).



**Step 6:** Align the GDS37XX with the bracket, press and push down the GDS37XX into place.




**Step 5:** Follow GDS37XX QIG and User Manual to connect wires to the PoE switch or PoE Injector. Connect the Electrical Lock wiring according to its document.



.7.

**Step 7:** Install the Cover Plate and fix it using the Hex Key with the Anti-Tamper Screws (5) provided.




.8.


## Stud Installation

Please follow below steps to install the device at the stud of a new building open wall, or a finished wall.


**Step 1:** For finished wall, use provided Drill Template to mark boundary and dig a rectangle hole into the wall. For open wall, skip and go to next step.




**Step 2:** Install the Metal Frame with short edge to the stud using the set of Anchor/Screw(1) provided.




**Step 3:** Mount the Installation Bracket into the Plastic Box using supplied Screws(2).




**Step 4:** Use provided Screws and Nuts(3)(4) to install the Plastic Box on the long edge of the Metal Frame. Choose either set of Nuts(4) with convenience.




**Step 5:** Remove the frame back cover (designed for Surface/ OnWall Installation).



**Step 7:** Align the GDS37XX with the bracket, press and push down the GDS37XX into place.




**Step 6:** Follow GDS37XX QIG and User Manual to connect wires to the PoE switch or PoE Injector. Connect the Electrical Lock wiring according to its document.



.11.

**Step 8:** Install the Cover Plate and fix it using the Hex Key with the Anti-Tamper Screws(5) provided.




.12.


## Drywall (Hollow Wall) Installation

Please follow below steps to install the device on a drywall or hollow wall. The thickness of the wall where the clamps can handle is among **6.2 ~ 24 mm (or 0.24 ~ 0.94 inch)**

**Step 1:** Use provided Drill Template to mark boundary then cut opening on the dry wall. **Do NOT over cut.** (wall cutting tools not provided)




**Step 2:** Mount the Installation Bracket into the Plastic Box using supplied Screws(2).




.13.

**Step 3:** Insert the Plastic Box into the cutted hole properly.




**Step 4:** Tighten the four clamps alternately in diagonal to mount the Plastic Box on the wall. Please do NOT over tighten to avoid damaging the wall or clamp.




.14.


**Step 5:** Remove the frame back cover (designed for Surface/ OnWall Installation).



**Step 7:** Align the GDS37XX with the bracket, press and push down the GDS37XX into place.




**Step 6:** Follow GDS37XX QIG and User Manual to connect wires to the PoE switch or PoE Injector. Connect the Electrical Lock wiring according to its document.



.15.

**Step 8:** Install the Cover Plate and fix it using the Hex Key with the Anti-Tamper Screws(5) provided.



(Result after installation.  
GDS37XX NOT included)

.16.